

RT38&RT638

FRS frequency 22 Channel & PMR446 16Channel

RETEVIS

Feature:

- Portable
- Ultrathin fuselage
- License free
- 121 code for each channel
- Transmit power:0.5W
- Channel scan
- With earphone jacket
- LCD Backlit display
- Dual channel monitor



RT38&RT638

FRS frequency 22 Channel & PMR446 16Channel

Electrical properties:

Receiving sensitivity:	-119 DBM@12dB
Signal-to-noise ratio:	68 DB
Spurious Resoince:	65dB
Audio output power:	0.25w
Noise Sensitivity:	-122+/-1dBm
Neighborhood selectivity:	63dB
Intermodulation Rejection:	62dB

Launch part:

Transmitting power :	0.5W
Maximum frequency deviation:	2.4KHZ
Adjacent channel power:	-65dB
Transmitting Audio Distortion:	<5%
Stray radiation:	-37dBm
Working current:	TX ≤ 350MA



Standard Accessories:

- RT38&RT638 two way radio
- 1*User Manual

CE FC RoHS 

Shenzhen Retevis Technology Co.,Ltd

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA