

H777 Plus

The Analog Two Way Radio

Features:

- CTCSS/DCS function
- Built-in Led torch
- Low battery alarm
- Power saving function
- PC software programmable
- Time-out-Time(TOT) function
- Scan function(be set via program software)
- Squelch level(be adjusted via program software)
- Voice prompt



H777 Plus

The Analog Two Way Radio

Receiver:

Sensitivity (12DB SINAD)	-122dBm
Adjacent Channel Selectivity	≥55dB@12.5KHz
intermodulation rejection	≥58dB
Rated audio power	≥0.5W@8ohms
Audio response	±1~-3db(0.3~3khz)
Rated audio distortion	≤5%

Transmitter:

output power	≤0.5 W
modulation mode	11K0F3E@12.5KHz
Modulation noise	≥40dB@12.5KHz
Stray radiation	-36dBm<1GHz, -30dBm>1GHz
Adjacent channel power	≤-60dB@12.5KHz
Audio response	±1~-3db(0.3~3khz)
Modulation distortion	≤3%

Standard Accessories:

- 1*H777 Plus Two Way Radio
- 1* Li-ion Battery
- 1*User Manual
- 1* Back clip
- 1*USB charger

CE FC RoHS 

Shenzhen Retevis Technology Co.,Ltd

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli

6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA