

RB18

Features:

- 1000mAh rechargeable lithium battery, support USB charging
- Frequency range: 462.5500-467.7125 MHz(RX&TX)
- Narrow band :12.5KHz
- Frequency step: 5K/6.25K/12.5K/25K
- Audio Output power: ≤2W(FRS)
- 50 groups analog CTCSS, 105 groups digital CDCSS
- 32 channels capacity (22FRS+10NOAA)
- Time out timer(TOT) (select 30-300s, 15 step)
- VOX feature and VOX level (1-5 grades)
- Busy Channel Lockout
- Squelch level(0-9 grades)
- Auto power saving function
- Monitor function
- Low power indication/alarm
- Chinese/English broadcasting function(PC programming or Basehand)
- Computer software program
- Frequency-hopping speech encryption
- Scan function
- 10 NOAA channels
- 2-pin Kenwood accessory port
- Flashlight function



RB18

Receiver:

Receive Sensitivity	0.25 μ V (12dB SINAD)
Adjacent Channel Selectivity	\geq 55dB@12.5KHz
intermodulation rejection	\geq 55dB@12.5KHz
Conducted Spurious Emission	\leq -57dB@12.5KHz
Rated Audio Power Output	0.75W @8ohms
Receive current	\leq 350mA
Rated Audio Distortion	\leq 5%

Transmitter:

RF Output Power	\leq 2W
FM Modulation	11K0F3E@12.5KHz
Spurious Emission	-36dBm < 1GHz, -30dBm > 1GHz
Adjacent Channel Power	60dB @ 12.5KHz
Transmission current	\leq 600mA

Standard Accessories:

- 1*RB18 Two Way Radio
- 1* Back clip
- 1* Li-ion Battery
- 1*USB charger
- 1*User Manual

CE FC RoHS 

Shenzhen Retevis Technology Co.,Ltd

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA