

RB627B/V

PMR446/Freenet Two way radio

RETCV IS

Feature:

- Indicator
- Channel Switch
- Power Switch
- Scan
- Monitor
- keypad lock
- A/B switch
- Flashlight and Emergency Alert
- FM Radio
- Power Saving Function
- Restore factory settings
- Squelch level (SQL)
- Beep tone
- VOX
- Dual Watch function



RB627B/V

PMR446/Freenet Two way radio

General Specifications

Frequency Range:	PMR446/Freenet
Operation Voltage:	DC3.7V ±10%
Battery Capacity:	1500mAH (Li-Ion)
Frequency Stability:	±2.5ppm
Operating Temperature:	20°C to +60°C
Mode of Operation:	Simplex
Antenna Impedance:	50ohm

Transmitter

FM Modulation:	11K0F3E@12.5KHz
Spurious Emission:	13dBm<1GHz, -13dBm>1GHz
Adjacent Channel Power:	60dB @ 12.5 KHz
Transmission current:	≤1200mA

Receiver

Receive Sensitivity:	0.25μV (12dB SINAD)
Adjacent Channel Selectivity:	≥55dB@12.5KHz
Inter Modulation and Rejection:	≥55dB@12.5KHz
Conducted Spurious Emission:	≤-57dB@12.5KHz
Receive current:	≤350mA
Rated Audio Distortion:	≤5%

Standard Accessories:

- 1x RB627B/V two way radio
- 1x Battery
- 1x Belt clip
- 1x Lanyard
- 1x USB Base
- 1x User Manual



CE FC RoHS



Shenzhen Retevis Technology Co.,Ltd.

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA