

# RETCVIS

## RT17&RT617

License Free / 16 Channels Two Way Radio

### Feature :

- Scanning
- Busy Channel Lock
- TOT(Time-out Timer)
- Squelch
- VOX Function
- CTCSS&DCS Encode/Decode
- Battery Save Function
- Scrambler Function



### Description:

This is the professional analog two way radio, rugged enclosure , wear resistance, not easy to scratch. one meter free fall, two way radio housing without damage, Good call quality, stable and reliable quality.

This two way radio is suitable for the storage, wharf, construction site, tourism, hotel, factory, etc.

# RT17&RT617

License Free / 16 Channels Two Way Radio

## General Specification

Frequency Range	US:FRS EU:PMR446
Power	2W/0.5W
Channel Capacity	16
Battery capacity	Li-ion 1200mAh
Working Voltage	DC 3.7V
Working Temperature	-10°C~50°C
Antenna Impedence	50Ω
Weight (with battery)	106g
Size	116*53*36mm

## Receiver

Sensitivity	≤0.2μV
Occupied Bandwidth	≤16KHz
Selectivity	≥65dB
Intermediation	≥55dB
Audio Power output	> 500mW
Modulation Distortion	≤10%
Frequency Stability	5ppm
Current	55mA(when standby)150mA(when working)
Audio Response	+7~-12.5dB

## Transmitter

Modulation type	FM
Spurious Radiation	≤0.75μW
Modulation Noise	<-40dB
Modulation Distortion	≤5%
Frequency Stability	5ppm
Maximum Deviation	≤±5KHz
Current	≤1200mA
Audio Response(300-3000Hz)	+6.5~-14dB
Adjacent Ch.power	≥65dB

## Package includes

- 2 x Radio
- 2 x Battery
- 2 x USB Charger
- 2 x Belt Clip
- 2 x Sling
- 1 x User manual



**Shenzhen Retevis Technology Co.,Ltd**

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli  
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: [www.retevis.com](http://www.retevis.com)

E-mail: [kam@retevis.com](mailto:kam@retevis.com)

Facebook: [facebook.com/retevis](https://facebook.com/retevis)



MADE IN CHINA